



## USB 16 Relay

**Item-No.:** UHR-16 Din-Rail-Module incl.  
**Item-No.:** UPR-16 only board

**Produktcode Taiwan:**  
AUSB16RELAY/PRO USB 16 RELAY OUTPUT BOARD W/TB PLUGS (whole set)  
AUSB16RELAY USB 16 RELAY OUTPUT BOARD

**Label on the card:**  
USB 16 RELAY OUTPUT BOARD  
DCI09040800

**Bus:** USB 2.0

**Description:** 16 SPDT-Relays - 1 x COM/NO/NC  
Maximum current 1000mA  
Maximum 30V  
  
16 LED correspond to I/O ports activation status.

**Connection:**



Easy exchange by interchangeable screw-terminals

### Features:

For direct DIN-Rail mounting  
Also as board without  
DIN-Rail-adapter available



High Speed 8051  $\mu$ C Core  
USB 2.0 Function Controller  
On-Chip Debug  
Support USB ID 0~14 SET  
POWER From USB OR DC+5V 0.5mA DC ADAPTOR (optional)

### Software/Driver:

Windows-XP Vista use HID-interface and sample for programming,  
Linux driver and sample for programming.

Per shipping you receive freshly burned „Decision Computer Germany  
service CD“ with current drivers, manuals, installation guidances and  
German additional information. The extent depends on the product!

**Operating temperature range:** from 0 to 33C.  
**Relative humidity rage:** from 0 to 90%.

### Package includes the following items:

USB 16 RELAY Board  
USB cable  
Software CD  
Englisch manual

**Size:** 250 mm x 120 mm x 55 mm

**Weight (Shipping):** 750 Gram  
**Weight (WEEE):** 500 Gram